BACKUP

SolarEdge Home Backup Interface Three Phase, for Europe

BI-EU3P



Flexible Backup Interface

- Automatically provides backup power to home loads in the event of grid interruption
- Flexibility in which loads to back up the entire home or selected loads
- Scalable solution to support higher power & higher capacity
- Seamless integration with the SolarEdge Home Hub Inverter to manage and monitor both PV generation and energy storage



/ SolarEdge Home Backup Interface Three Phase, for Europe

BI-EU3P

	BI-EU3P ⁽¹⁾	UNITS
GRID CONNECTION		
AC Current Input	3*63	A
AC Voltage Line – Neutral (Min/Nom/Max)	184/230/264	V
AC Frequency Range	50/60	Hz
On Grid to Off Grid Switchover Time	< 3	Sec
OUTPUT TO DISTRIBUTION PANEL		
Maximum AC Current Output	3*63	A
AC Voltage Line – Neutral (Min/Nom/Max)	184/230/264	V
AC Frequency Range	50/60	Hz
Overvoltage Category	III	
ADDITIONAL FEATURES		
Supported Grid Topologies	TT, TN-S, TN-C-S ⁽²⁾	
Operation During Backup	Disconnection of 3 phases + N from external grid;	
<u> </u>	PE to Neutral connection on load side / disconnection configuration option on internal grid	
Number of Communication Inputs Communication	RS485 and SolarEdge Home Network ⁽³⁾	
	Ÿ	
Energy Meter (for Import/Export)	Integrated ⁽³⁾ , 1.25% accuracy	
Manual Control Over Microgrid Interconnection Device	Yes	
STANDARD COMPLIANCE		
Safety	IEC/EN 62109-1	
Emissions	IEC 61000-6-2, IEC 61000-6-3, IEC 61000-3-11, IEC 61000-3-12, EN55011	
INSTALLATION SPECIFICATIONS		
Supported Inverters	SolarEdge Home Hub Inverter – Three Phase	
Grid / Loads Conductor Cross Section	6 – 25	mm ²
Grid / Loads Conduit Diameter	14 – 22	mm
Communication Cable Cross Section	0. 2 – 1.5	mm^2
Communication Gland Diameter	5 – 15	mm
Weight	< 5	kg
Noise	< 50	dBA
Operating Temperature Range	-40 to +50	°C
Relative Humidity Range	0 – 100	%
Protection Rating	IP65	
Dimensions (H x W x D)	390 x 238 x 147	mm
Environmental Category	Outdoor	
Pollution Degree	3	
Maximum Altitude Rating	2000	m

⁽¹⁾ Applicable for PN BI-NEUNU-3P-01.

⁽²⁾ For other topologies please contact SolarEdge support.

⁽³⁾ Pending firmware support.